Tonelify

CHEAT SHEET

Hughes & Kettner TubeMeister 18 Settings Cheat Sheet

Clock positions. The first row is H&K's own start; the other four are Tonelify's.

	POWER SOAK	BASS	MID	TREBLE	CLEAN GAIN	CLEAN MASTER	LEAD GAIN	LEAD MASTER	LEAD BOOST SWITCH
H&K start POWER SOAK 5 W, ALL AT 12:00	5 W	12:00	12:00	12:00	12:00	12:00	12:00	12:00	
Clean CLEAN CHANNEL, 18 W	18 W	12:00	11:00	1:00	10:00	1:00			
Crunch CLEAN CHANNEL, 5 W	5 W	12:00	1:00	12:00	2:00	11:00			
Rock lead LEAD, BOOST OFF, 1 W	1 W	12:00	1:00	12:00			12:00	3:00	off
Metal LEAD, BOOST ON, 18 W	18 W	1:00	11:00	1:00			3:00	10:00	on

VOLUME	Set the loudness with the Power Soak.
QUIET	Lead Master at zero still sounds: use 1 W.
CLEAN	Clean Gain breaks up near 12:00.
BOOST	Lead Boost re-voices for high gain.
RECORD	Speaker off plus Red Box = silent.
OHMS	Cabinets 8 to 16 ohms in total.